

# Luxi RHB-350 switcher Tx RS-232 commands

Rev 1.00

Function	Command to RHB-350	Response from RHB-350	Notes	Factory default
<b>Product information commands</b>				
Query device part number	<i>p</i>	74-037-01¶	Numeric and dash only	
MCU firmware version	<i>1P</i>	x.xx¶	Numeric only	
HDBT firmware version	<i>4P</i>	x.xx¶	Numeric only	

**RS-232 baud rate/protocol**      **9600 baud, 8 data bits, 1 stop bit, no parity**  
**RS-232 port pin configurations**      **1 = Tx, 2 = Rx, 3 = GND**

Note: The italic and underlined letters represent decimal numeric numbers  
 ¶ is CR/LF (carriage return/line feed) (HEX value 0D 0A)

Not all firmware revisions have all the functions  
 Copyright C 2017 Luxi Electronics Corp